



Full Boar 4 Lighting Control Console

- Operating System: Hog 4 OS
- Built in DMX Processor 8000
- Built-in Kensington Security Lock
- USB Recovery Flash Drive Included
- USB Flash Drive for Show file storage included
- Desklights included
- Light Converse Visualizer dongle included
- Dust cover included
- Custom Road Case Included

CONTROL SURFACE:

Playback Faders: 10, motorized
GrandMaster: dedicated, motorized
DBO Key: dedicated, toggle on/off
Encoder Wheels: 5 with dedicated function buttons
Function Keys: 12 keys with dedicated LCD displays
KeyBoard: Support for external USB keyboard
Trackball: Built-in backlit trackball with rotary encoder
Desklight: 2, dimmable blue and white LEDs
Worklight: Yes, dimmable white
Ventlight: Yes, dimmable blue

ELECTRICAL

Voltage: 100-240VAC, 50 / 60Hz
Max Current: 4A
Mains Connector: IEC 320

PHYSICAL

Weight: 45 lbs (20.41 kg)
Dimensions: 35.49" (901.19mm) wide
22.65" (575.36mm) deep
9.62" (244.34mm) high

DISPLAYS

Internal: Two 15.6" widescreen touchscreens
(both touchscreens are 10 point multi-touch)
External: Support for two monitors / touchscreens
(DVI-D)
(see Hog4OS manual for list of supported touchscreens)

DMX / ARTNET / SCAN

Local Output Processing: 12 universes (6,144 ch)
Local DMX Outputs: 4 x Neutrik 5-pin female XLR
Expansion via external DP8000s: Yes, Unlimited

I/O CONNECTIVITY

USB 2.0 Ports: 4 rear
USB 3.0 Ports: 1 top
HogNet: Yes (allows connectivity to other consoles)
FixtureNet: Yes (Art-Net, sACN, Visualizer connect)
Onboard MIDI: In/Out/Thru
(supports MIDI Show Control, MIDI Timecode, and MIDI Notes)
Onboard LTC: Input via 3-pin XLR
Visualizer connectivity: FixtureNet / Art-Net / sACN
(list of supported visualizers in Hog 4 OS help manual)
Remote Focus: Yes, via Open Sound Control

COMPUTER

Motherboard: Advantech AIMB-581
Processor: Intel Core i3-2120 3.3Ghz
Memory: 8 GB
Internal Hard Drive: 32 GB SSD
Internal CD-R/DVD-ROM: No